



Victron energy power inverters

Victron energy power inverters

The Victron MultiPlus combines a powerful pure sine wave inverter with a sophisticated battery charger and a high-speed AC transfer switch encapsulated in a single compact enclosure. The Multiplus can take an input from a generator or grid supply. It can be used in conjunction with a battery bank and solar PV inverter as an energy storage system. Up to 6 Multiplus units can operate in parallel to achieve higher power output. Three phase or split phase operation is also possible.

Victron are a global leader in off-grid and battery storage systems, with over 40 years of expertise in the fields of renewable energy and portable power systems. Installation is a simple matter using the detailed instruction manual with fully illustrated colour wiring and mounting diagrams. The true benefit of the Multiplus is the software functionality and advanced protection systems, with regular firmware updates constantly adding new features as and when the community request them.

Proven reliability: The full bridge plus toroidal transformer topology has proven its reliability over many years. The inverter is short circuit proof and protected against overheating, whether due to overload or high ambient temperature.

PowerControl - Dealing with limited generator, shore side or grid power: With the Multi Control Panel a maximum generator or shore current can be set. The MultiPlus will then take account of other AC loads and use whatever is extra for charging, thus preventing the generator or shore supply from being overloaded.

PowerAssist - Boosting the capacity of shore or generator power: Where peak power is so often required only for a limited period, the MultiPlus will make sure that insufficient shore or generator power is immediately compensated for by power from the battery. When the load reduces, the spare power is used to recharge the battery.

Search Mode: When Search Mode is 'on', the power consumption of the inverter in no-load operation is decreased by approx. 70%. In this mode the Multi, when operating in inverter mode, is switched off in case of no load or very low load, and switches on every two seconds for a short period. If the output current exceeds a set level, the inverter will continue to operate. If not, the inverter will shut down again.

Programmable relay: By default, the programmable relay is set as an alarm relay, i.e. the relay will de-energise in the event of an alarm or a pre-alarm (inverter almost too hot, ripple on the input almost too high, battery voltage almost too low).

The Victron Phoenix Inverter 12/2000 is a pure sine wave inverter that converts 12 volts DC to 230 volts AC. It has a maximum power output of 2000 watts and is equipped with smart features for efficient energy management.



Victron energy power inverters

Key features: Low voltage alarm Low voltage cut off & restart levels Dynamic cut-off : Load dependant cut-off level Output voltage 210 - 245V Eco mode on/off and ECO mode sense level Alarm relay Details: Pure Sine Wave Output 4000VA Peak Power 2000 VA Continuous Zero Load - 8W Zero Load ECO Mode - 0.6W VE. Direct communication port Dimensions h485 x w219 x d125 mm 13 kg in weight 5 Year Warranty

Contact us for free full report

Web: <https://sumthingtasty.co.za/contact-us/>

Email: energystorage2000@gmail.com

WhatsApp: 8613816583346

